

## **Technical Data Sheet**

### **Features**

- Package in 8mm tape on 7" diameter reel.
- Compatible with automatic placement equipment.
- Compatible with infrared and vapor phase reflow solder process.
- Bi-color type.
- Color: Yellow & Red.
- The product itself will remain within RoHS compliant Version.

### **Descriptions**

The S195 SMD LED is much smaller than lead frame type components, thus enable smaller board size, higher packing density, reduced storage space and finally smaller equipment to be obtained.

Besides, lightweight makes them ideal for miniature applications, etc.



### **Applications**

- Backlighting in dashboard and switch.
- Telecommunication: Indicator and backlighting in telephone and fax.
- Flat backlight for LCD, switch and symbol.
- General use.


**Technical Data Sheet**

Part No.	Emitting Color		Lens Color
S195YVC-3C-E2BS	V	Red	Water Clear
	Y	Yellow	


**Package Dimension:**



**Polarity**



**Recommended Soldering Pad Dimensions**



**Notes:**

1. All dimensions are in millimeters (inches).
2. Tolerance is  $\pm 0.25$  mm (.010") unless otherwise noted.

**Surface Mount Bi-Color Chip LED Indicator**

**Technical Data Sheet**

**Absolute Maximum Ratings at Ta=25°C**

Parameters	Symbol	Emitting Color	Max.	Unit
Power Dissipation	PD	Red	60	mW
		Yellow	60	
Peak Forward Current <sup>(a)</sup>	IFP	Red	100	mA
		Yellow	100	
Continuous Forward Current <sup>(b)</sup>	IF	Red	25	mA
		Yellow	25	
Reverse Voltage	VR		5	V
Electrostatic Discharge (HBM)	ESD	Red	2000	V
		Yellow	2000	
Operating Temperature Range	Topr		-40°C to +85°C	
Storage Temperature Range	Tstg		-40°C to +85°C	
Soldering Temperature	Tsld		260°C for 5 Seconds	

Notes:

- a. Duty Factor = 10%, Frequency = 1 kHz
- b. Derate linearly as shown in derating curve.

**Technical Data Sheet**

**Electrical Optical Characteristics at Ta=25°C**

Parameters	Symbol	Emitting Color	Min.	Typ.	Max.	Unit	Test Condition
Luminous Intensity <sup>(a)</sup>	IV	Red	150	220	---	mcd	IF=20mA
		Yellow	230	350	---		
Viewing Angle	2θ1/2	Red	---	140	---	Deg	IF=20mA
		Yellow	---	140	---		
Peak Emission Wavelength	λp	Red	---	632	---	nm	IF=20mA
		Yellow	---	592	---		
Dominant Wavelength <sup>(b)</sup>	λd	Red	---	624	---	nm	IF=20mA
		Yellow	---	590	---		
Spectral Line Half-Width	△λ	Red	---	20	---	nm	IF=20mA
		Yellow	---	20	---		
Forward Voltage <sup>(c)</sup>	VF	Red	1.60	2.00	2.40	V	IF=20mA
		Yellow	1.60	2.00	2.40		
Reverse Current	IR	Red	---	---	10	μA	VR=5V
		Yellow	---	---	10		







Notes:

- a. Luminous Intensity measurement tolerance: ±10%.
- b. Wavelength measurement tolerance: ±1nm
- c. Forward voltage measurement tolerance: ±0.1V

**Surface Mount Bi-Color Chip LED Indicator**

**Technical Data Sheet**


**Typical Electrical / Optical Characteristics Curves**  
**(25°C Ambient Temperature Unless Otherwise Noted)**



**Surface Mount Bi-Color Chip LED Indicator**


**Technical Data Sheet**

**Reel Dimensions**



**Carrier Tape Dimensions**


Loaded quantity 4000 pcs per reel.



## Technical Data Sheet

### Packing & Label Specifications

Moisture Resistant Packaging




**Surface Mount Bi-Color Chip LED Indicator**

**Technical Data Sheet**

**CAUTIONS**

**1. Handling Precautions:**

- 1.1. Handle the component along the side surfaces by using forceps or appropriate tools.
- 1.2. Do not directly touch or handle the silicone lens surface. It may damage the internal circuitry.
- 1.3. Do not stack together assembled PCBs containing exposed LEDs. Impact may scratch the silicone lens or damage the internal circuitry.



Compare to epoxy encapsulant that is hard and brittle, silicone is softer and flexible. Although its characteristic significantly reduces thermal stress, it is more susceptible to damage by external mechanical force. As a result, special handling precautions need to be observed during assembly using silicone encapsulated LED products. Failure to comply might lead to damage and premature failure of the LED.


**2. Storage**

- 2.1. Do not open moisture proof bag before the products are ready to use.
- 2.2. Before opening the package, the LEDs should be kept at 30°C or less and 60%RH or less.
- 2.3. The LEDs should be used within a year.
- 2.4. After opening the package, the LEDs should be kept at 30°C or less and 60%RH or less.
- 2.5. The LEDs should be used within 168 hours after opening the package.
- 2.6. If the moisture adsorbent material has fabled away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions. Baking treatment: 65±5°C for 24 hours.

## Technical Data Sheet

### 3. Soldering Condition

#### 3.1. Pb-free solder temperature profile



3.2. Reflow soldering should not be done more than two times.

3.3. When soldering, do not put stress on the LEDs during heating.

3.4. After soldering, do not warp the circuit board.

3.5. Recommended soldering conditions: [\[L\]](#) [\[SEP\]](#)

Reflow soldering		Soldering iron	
Pre-heat	150~200°C	Temperature	300°C Max.
Pre-heat time	120 sec. Max.	Soldering time	3 sec. Max.
Peak temperature	260°C Max.		(one time only)
Soldering time	10 sec. Max.(Max. two times)		


3.6. Because different board designs use different number and types of devices, solder pastes, reflow ovens, and circuit boards, no single temperature profile works for all possible combinations.

However, you can successfully mount your packages to the PCB by following the proper guidelines and PCB-specific characterization.

## **Technical Data Sheet**

### **4. Drive Method**

4.1. An LED is a current-operated device. In order to ensure intensity uniformity on multiple LEDs connected in parallel in an application, it is recommended that a current limiting resistor be incorporated in the drive circuit, in series with each LED as shown in Circuit A below.



- Recommended circuit.
- The brightness of each LED might appear different due to the differences in the I-V characteristics of those LEDs.

### **Terms and conditions for the usage of this document**

- The information included in this document reflects representative usage scenarios and is intended for technical reference only.
- The part number, type, and specifications mentioned in this document are subject to future change and improvement without notice. Before production usage customer should refer to the latest datasheet for the updated specifications.
- When using the products referenced in this document, please make sure the product is being operated within the environmental and electrical limits specified in the datasheet. If customer usage exceeds the specified limits, Luckylight will not be responsible for any subsequent issues.
- The information in this document applies to typical usage in consumer electronics applications. If customer's application has special reliability requirements or have life-threatening liabilities, such as automotive or medical usage, please consult with Luckylight representative for further assistance.
- The contents and information of this document may not be reproduced or re-transmitted without permission by Luckylight.